

**VSC WARNING LIGHT CIRCUIT (DOES NOT LIGHT UP)**

**INSPECTION PROCEDURE**

**1 INSPECT CAN COMMUNICATION SYSTEM (SEE PAGE 05-2605)**

(a) Is the DTC output for CAN communication system?

**Result:**

DTC is not output	A
DTC is output	B

**B** REPAIR CAN COMMUNICATION SYSTEM (SEE PAGE 05-2619)

**A**

**2 INSPECT MULTIPLEX COMMUNICATION SYSTEM (SEE PAGE 05-2549)**

(a) Is the DTC output for Multiplex communication system?

**Result:**

DTC is not output	A
DTC is output	B

**B** REPAIR MULTIPLEX COMMUNICATION SYSTEM (SEE PAGE 05-2558)

**A**

**REPAIR OR REPLACE COMBINATION METER ASSY (SEE PAGE 05-1986)**