

ABS WARNING LIGHT CIRCUIT (DOES NOT LIGHT UP)

INSPECTION PROCEDURE

1 INSPECT CAN COMMUNICATION SYSTEM (SEE PAGE 05-2605)

(a) Is the DTC output for CAN communication system?

Result:

DTC is not output	A
DTC is output	B

B REPAIR CAN COMMUNICATION SYSTEM (SEE PAGE 05-2619)

A

2 INSPECT MULTIPLEX COMMUNICATION SYSTEM (SEE PAGE 05-2549)

(a) Is the DTC output for Multiplex communication system?

Result:

DTC is not output	A
DTC is output	B

B REPAIR MULTIPLEX COMMUNICATION SYSTEM (SEE PAGE 05-2558)

A

REPAIR OR REPLACE COMBINATION METER ASSY (SEE PAGE 05-1986)